

SPECIFICATION SHEET

Item Number **0152511**

Saf-T-Bar®

For New Construction Applications

Specifications

Attic Access Required

- Can be used with engineered truss
- · Fits all ceiling fans
- Fits 16" to 24" ceiling joists
- For fixture support of 150 lbs. or less on 16" centers
- For fixture support of 90 lbs. or less on 24" centers
- Acceptable for fan support of 70 lbs. or less
- · Position box anywhere along the brace
- Heavy duty, all metal, dual mount* electrical box
- 1-1/2" box depth, 15.5 cubic inch wiring capacity
- Six 1/2" Romex® or conduit knockouts; 1 Romex® connector
- Includes Saf-T-Cap* to protect inner workings during drywall installation or painting
- · Includes mounting hardware and instructions



Pack Information

- Bulk Packed
- 12 Per Cut Case







Meets or Exceeds UL Standards Regarding Exposed Threads Within Box. Meets or Exceeds NEC Safety Codes.

Romex® is a registered trademark of Southwire Company.

Specifications are subject to change without notice, please visit www.westinghouselighting.com for latest information.

Call 1-800-999-2226 or visit www.westinghouselighting.com.

(W), WESTINGHOUSE, and INNOVATION YOU CAN BE SURE OF are trademarks of Westinghouse Electric Corporation. Used under license by Westinghouse Lighting. All Rights Reserved.

2018 WESTINGHOUSE LIGHTING / 0518

^{*}Dual Mount = Box is threaded for #8-32 (ideal for box covers and lightweight fixtures) and #10-24 screws (ideal for heavier fixtures and ceiling fans).



SPECIFICATION SHEET

Item Number **0152511**

Saf-T-Bar®

For New Construction Applications

Specifications

Attic Access Required

- Can be used with engineered truss
- · Fits all ceiling fans
- Fits 16" to 24" ceiling joists
- For fixture support of 150 lbs. or less on 16" centers
- For fixture support of 90 lbs. or less on 24" centers
- Acceptable for fan support of 70 lbs. or less
- · Position box anywhere along the brace
- Heavy duty, all metal, dual mount* electrical box
- 1-1/2" box depth, 15.5 cubic inch wiring capacity
- Six 1/2" Romex® or conduit knockouts; 1 Romex® connector
- Includes Saf-T-Cap* to protect inner workings during drywall installation or painting
- · Includes mounting hardware and instructions



Pack Information

- Bulk Packed
- 12 Per Cut Case







Meets or Exceeds UL Standards Regarding Exposed Threads Within Box. Meets or Exceeds NEC Safety Codes.

Romex® is a registered trademark of Southwire Company.

Specifications are subject to change without notice, please visit www.westinghouselighting.com for latest information.

Call 1-800-999-2226 or visit www.westinghouselighting.com.

(W), WESTINGHOUSE, and INNOVATION YOU CAN BE SURE OF are trademarks of Westinghouse Electric Corporation. Used under license by Westinghouse Lighting. All Rights Reserved.

2018 WESTINGHOUSE LIGHTING / 0518

^{*}Dual Mount = Box is threaded for #8-32 (ideal for box covers and lightweight fixtures) and #10-24 screws (ideal for heavier fixtures and ceiling fans).