

# Stinger® LED Rechargeable Flashlight

Case Material: 6000 series machined aircraft aluminum with non-slip rubberized comfort grip and anti-roll rubber ring.

Dimensions: Length: 8.41 in. (21.36 cm) Diameter: Major Diameter: 1.62 in. (4.11 cm)  
Body Diameter: 1.17 in. (2.97 cm)

Weight: 12.4 oz (352 grams)\*

Lens: Unbreakable polycarbonate lens with scratch-resistant coating

Light Source: C4 LED technology, shock-proof with a 50,000 hour lifetime.

Light Output: Up to 18,000 candela (peak beam intensity); up to 160 lumens measured system output. Deep-dish parabolic reflector produces a long range targeting beam with optimum peripheral illumination to aid in navigation. Optimized electronics provides regulated intensity.

On/Off: Multi-function, easy access push-button switch designed for extremely long life; tested at 1 million actuations

Run Time: High brightness: 1.75 continuous hours  
Medium brightness: 3.5 continuous hours  
Low brightness: 6.75 continuous hours

Battery: 3-Cell, 3.6-Volt Nickel-cadmium sub-C battery is rechargeable up to 1000 times

Charging: Ten hours to fully recharge on 100V, 120V, 230V or 240V AC, or 12V DC, 2.5-hour fast charger or PiggyBack® charger model available

Features: • Anti-roll ring included • LED charge-continuity indicator, compact  
• Snap-in charger holder that mounts in any position • Serialized for positive identification

Approvals\*\*: Most models meet applicable European Community Directives.

Warranty: Limited lifetime warranty

\*With battery (included in purchase).

\*\*See product for specific ratings.



| Item                                    | UPC            | Part # |
|---|----------------|--------|
| Steady Charge AC/DC - 2 Holders         |                |        |
| Stinger LED with 230V                   | 080926-75725-7 | 75725  |
| Stinger LED with 240V                   | 080926-75729-5 | 75729  |
| Stinger LED with 120V                   | 080926-75713-4 | 75713  |
| Stinger LED with 100V                   | 080926-75718-9 | 75718  |
| AC Only                                 |                |        |
| Stinger LED with 230V                   | 080926-75724-0 | 75724  |
| Stinger LED with 240V                   | 080926-75728-8 | 75728  |
| Stinger LED with 120V                   | 080926-75711-0 | 75711  |
| Stinger LED with 100V                   | 080926-75717-2 | 75717  |
| DC Only                                 |                |        |
| Stinger LED with DC                     | 080926-75712-7 | 75712  |
| Stinger LED with DC PiggyBack           | 080926-75734-9 | 75734  |
| Stinger LED with DC Fast Charger        | 080926-75715-8 | 75715  |
| Stinger LED with DC - FC PiggyBack      | 080926-75737-0 | 75737  |
| Steady Charge AC/DC PiggyBack           |                |        |
| Stinger LED with 230V                   | 080926-75739-4 | 75739  |
| Stinger LED with 240V                   | 080926-75743-1 | 75743  |
| Stinger LED with 120V                   | 080926-75732-5 | 75732  |
| Stinger LED with 100V                   | 080926-75732-5 | 75746  |
| AC - PiggyBack Holder                   |                |        |
| Stinger LED with 230V                   | 080926-75738-7 | 75738  |
| Stinger LED with 240V                   | 080926-75742-2 | 75742  |
| Stinger LED with 120V                   | 080926-75733-2 | 75733  |
| Stinger LED with 100V                   | 080926-75721-9 | 75721  |
| See reverse for additional part numbers |                |        |

| Item                                    | UPC            | Part # |
|---|----------------|--------|
| AC/DC Fast Charger - 2 Holders          |                |        |
| Stinger LED with 230V                   | 080926-75727-1 | 75727  |
| Stinger LED with 240V                   | 080926-75731-8 | 75731  |
| Stinger LED with 120V                   | 080926-75735-6 | 75735  |
| Stinger LED with 100V                   | 080926-75720-2 | 75720  |
| AC Fast Charger                         |                |        |
| Stinger LED with 230V                   | 080926-75726-4 | 75726  |
| Stinger LED with 240V                   | 080926-75730-1 | 75730  |
| Stinger LED with 120V                   | 080926-75714-1 | 75714  |
| Stinger LED with 100V                   | 080926-75719-6 | 75719  |
| AC/DC - Fast Charger PiggyBack Holder   |                |        |
| Stinger LED with 230V                   | 080926-75741-7 | 75741  |
| Stinger LED with 240V                   | 080926-75716-5 | 75745  |
| Stinger LED with 120V                   | 080926-75716-5 | 75716  |
| Stinger LED with 100V                   | 080926-75747-9 | 75747  |
| AC - Fast Charger PiggyBack Holder      |                |        |
| Stinger LED with 230V                   | 080926-75740-0 | 75740  |
| Stinger LED with 240V                   | 080926-75744-8 | 75744  |
| Stinger LED with 120V                   | 080926-75736-3 | 75736  |
| Stinger LED with 100V                   | 080926-75722-6 | 75722  |
| (WITHOUT CHARGER)                       |                |        |
| Stinger LED                             | 080926-75710-3 | 75710  |
| See reverse for additional part numbers |                |        |

# Stinger® LED Rechargeable Flashlight

Case Material: 6000 series machined aircraft aluminum with non-slip rubberized comfort grip and anti-roll rubber ring.

Dimensions: Length: 8.41 in. (21.36 cm) Diameter: Major Diameter: 1.62 in. (4.11 cm)  
Body Diameter: 1.17 in. (2.97 cm)

Weight: 12.4 oz (352 grams)\*

Lens: Unbreakable polycarbonate lens with scratch-resistant coating

Light Source: C4 LED technology, shock-proof with a 50,000 hour lifetime.

Light Output: Up to 18,000 candela (peak beam intensity); up to 160 lumens measured system output. Deep-dish parabolic reflector produces a long range targeting beam with optimum peripheral illumination to aid in navigation. Optimized electronics provides regulated intensity.

On/Off: Multi-function, easy access push-button switch designed for extremely long life; tested at 1 million actuations

Run Time: High brightness: 1.75 continuous hours  
Medium brightness: 3.5 continuous hours  
Low brightness: 6.75 continuous hours

Battery: 3-Cell, 3.6-Volt Nickel-cadmium sub-C battery is rechargeable up to 1000 times

Charging: Ten hours to fully recharge on 100V, 120V, 230V or 240V AC, or 12V DC, 2.5-hour fast charger or PiggyBack® charger model available

Features: • Anti-roll ring included • LED charge-continuity indicator, compact  
• Snap-in charger holder that mounts in any position • Serialized for positive identification

Approvals\*\*: Most models meet applicable European Community Directives.

Warranty: Limited lifetime warranty

\*With battery (included in purchase).

\*\*See product for specific ratings.



| Item                                    | UPC            | Part # |
|---|----------------|--------|
| Steady Charge AC/DC - 2 Holders         |                |        |
| Stinger LED with 230V                   | 080926-75725-7 | 75725  |
| Stinger LED with 240V                   | 080926-75729-5 | 75729  |
| Stinger LED with 120V                   | 080926-75713-4 | 75713  |
| Stinger LED with 100V                   | 080926-75718-9 | 75718  |
| AC Only                                 |                |        |
| Stinger LED with 230V                   | 080926-75724-0 | 75724  |
| Stinger LED with 240V                   | 080926-75728-8 | 75728  |
| Stinger LED with 120V                   | 080926-75711-0 | 75711  |
| Stinger LED with 100V                   | 080926-75717-2 | 75717  |
| DC Only                                 |                |        |
| Stinger LED with DC                     | 080926-75712-7 | 75712  |
| Stinger LED with DC PiggyBack           | 080926-75734-9 | 75734  |
| Stinger LED with DC Fast Charger        | 080926-75715-8 | 75715  |
| Stinger LED with DC - FC PiggyBack      | 080926-75737-0 | 75737  |
| Steady Charge AC/DC PiggyBack           |                |        |
| Stinger LED with 230V                   | 080926-75739-4 | 75739  |
| Stinger LED with 240V                   | 080926-75743-1 | 75743  |
| Stinger LED with 120V                   | 080926-75732-5 | 75732  |
| Stinger LED with 100V                   | 080926-75732-5 | 75746  |
| AC - PiggyBack Holder                   |                |        |
| Stinger LED with 230V                   | 080926-75738-7 | 75738  |
| Stinger LED with 240V                   | 080926-75742-2 | 75742  |
| Stinger LED with 120V                   | 080926-75733-2 | 75733  |
| Stinger LED with 100V                   | 080926-75721-9 | 75721  |
| See reverse for additional part numbers |                |        |

| Item                                    | UPC            | Part # |
|---|----------------|--------|
| AC/DC Fast Charger - 2 Holders          |                |        |
| Stinger LED with 230V                   | 080926-75727-1 | 75727  |
| Stinger LED with 240V                   | 080926-75731-8 | 75731  |
| Stinger LED with 120V                   | 080926-75735-6 | 75735  |
| Stinger LED with 100V                   | 080926-75720-2 | 75720  |
| AC Fast Charger                         |                |        |
| Stinger LED with 230V                   | 080926-75726-4 | 75726  |
| Stinger LED with 240V                   | 080926-75730-1 | 75730  |
| Stinger LED with 120V                   | 080926-75714-1 | 75714  |
| Stinger LED with 100V                   | 080926-75719-6 | 75719  |
| AC/DC - Fast Charger PiggyBack Holder   |                |        |
| Stinger LED with 230V                   | 080926-75741-7 | 75741  |
| Stinger LED with 240V                   | 080926-75716-5 | 75745  |
| Stinger LED with 120V                   | 080926-75716-5 | 75716  |
| Stinger LED with 100V                   | 080926-75747-9 | 75747  |
| AC - Fast Charger PiggyBack Holder      |                |        |
| Stinger LED with 230V                   | 080926-75740-0 | 75740  |
| Stinger LED with 240V                   | 080926-75744-8 | 75744  |
| Stinger LED with 120V                   | 080926-75736-3 | 75736  |
| Stinger LED with 100V                   | 080926-75722-6 | 75722  |
| (WITHOUT CHARGER)                       |                |        |
| Stinger LED                             | 080926-75710-3 | 75710  |
| See reverse for additional part numbers |                |        |